



Remote access controller with built-in RF receiver

PR-6750V



Product Description

PR-6750V is a on-line remote access controller with built-in RF receiver. It can be used with electric lock as access control system or with relay box and Key transmitter (Four keys) as car parking system. Optional transmitter (PTM series) with embedded RFID chip can be applied to both parking and access control system. The transmitter capacity: **1,000~32,000**pcs

Features

- With hopping code anti-copied remote access controller , transmitter capacity : **1,000~32,000**pcs. (Depending on the model)
- With **up .stop .down** and **power outage** relay, combination relay box with key transmitter (Four keys) as car parking system.
- If the transmitter is copied, hopping code will be no response if you press it.
- You can add/delete the transmitter authorization upon your request by manual control or on-line with PC, and recording OUT/IN time.

Specification

Dimensions(L x W x H)mm	: 137 x 85 x 29
Net weight	: 340g ± 5%
Power supply	: DC 12V±10%, 80mA(Standby) 100mA(Working)
Reading range	: 15 m
Frequency of operation	: 433.9MHz
Operating temperature	: 0oC ~ 70oC
Operating humidity	: 10%~90%

How to order

Access control system:

PR-6750V	Remote access controller
PTX-201	Key transmitter (Signal key)
Electric lock	Electric strike lock / Electric dropbolt / Electromagnetic locks

Car parking system:

PR-6750V	Remote access controller
PTX-204	Key transmitter (Four key)
PG-OUTMOD-4	Relay box